


AXIS T8127 60 W Splitter 12/24 V DC

For 12 or 24 V DC installations

A splitter is used to split the power and data in an Ethernet cable into two separate cables, which then can be connected to a network device that has no built-in support for Power over Ethernet (PoE). AXIS T8127 60 W Splitter 12/24 V DC enables Axis' network products and accessories, such as Axis' illuminators, media converters etc.. to receive 12 or 24 V DC with up to 4.5A. The splitter can be powered from any Axis midspan or PoE switch. AXIS T8127 offers an easy, fast and cost-effective solution compared with adding a power supply to your system.

- > [For Axis network products and accessories](#)
- > [High power](#)
- > [Reduced installation costs](#)
- > [Plug-and-play](#)



AXIS T8127 60 W Splitter 12/24 V DC

| General | |
|--------------------------------------|--|
| Environment | Indoor |
| Dimensions | 38 x 73 x 130 mm (1.5 x 2.9 x 5.1 in) |
| Weight | 285 g (0.6 lb) |
| Power | Input power: Max 70 W Output power: Max 54 W Output current at 12 V DC: 4.5 A Output current at 24 V DC: 2.25 A |
| Connectors | Data Et power in: RJ45 10BASE-T/100BASE-TX/1000BASE-T PoE Data out: RJ45 10BASE-T/100BASE-TX/1000BASE-T Voltage switch selector (12/24 V DC) Power out: DC barrel connector 3.4 x 1.35 mm Internal pole: Positive (+) V DC External pole: Negative (-) V DC |
| Operating conditions | 0 °C to 40 °C (32 °F to 104 °F) Humidity 0–90% RH (non-condensing) |
| Storage conditions | -40 °C to 65 °C (-40 °F to 149 °F) |
| Approvals | EN 55022 Class B EN 55024 FCC Part 15 Subpart B Class B ICES-003 Class B VCCI Class B CE WEEE RoHS |
| Included accessories | Installation Guide Power cord cable Cover sticker |
| Warranty | Axis 3-year warranty, see www.axis.com/warranty |
| Environmental responsibility: | www.axis.com/environmental-responsibility |