
## YV2.2×1.4A-SA2






















- Fish-Eye vari-focal lens with the horizontal field angle of 185-94 degrees (when used on 1/3 cameras).
- Wide aperture of F1.4, optimizing the performance at low lighting intensity.
- Built-in ND filter of T360, supporting high sensitivity cameras.

130 <sup>130</sup> IRIS CONTROL CABLE	49.8  49.8  49.8  49.8  49.10:20  49.10:20  44.2
(CONNECTOR : 4-PIN PLUG)	Unit : mm

Focal Length (mm)			1.4~3.1 (2.2×)
Iris Range			F1.4 ~ T360 (Equivalent to F360)
Zoo		om	Manual
Operation	Focus		Manual
	Iris		Auto (DC Type) (*1)
Angle Of View (HXV)	1/3"	WIDE	185° (¢3.45)
		TELE	94°47′ × 69°26′
	1/4"	WIDE	185° × 121°
		TELE	69°26′ × 51°30′
Focusing Range (From Front Of The Lens) (m)			∞ ~ 0.2
Object	1/3"	WIDE	_
Dimensions		TELE	448 × 287
at M.O.D. (H×V) (mm)	1/4"	WIDE	_
		TELE	287 × 200
Back Focal Distance (in air) (mm)			7.82
Exit Pupil Position (From Image Plane) (mm)			-45
Filter Thread (mm)			_
Mount			CS
Mass (g)			80
Coil Resistance			Drive Coil 200Ω
		•	Damping Coil 600Ω
Current Consumption		tion	22mA (Max.) at DC 4V
Remarks			(*1) When power is turned off, iris will
			automatically close.
			YV2.2×1.4A-SA2L:
			Long Cable Type (230mm)



[Fish-Eye Lens Image]



1/4"

